



HEATIT Z-PUSH WALL CONTROLLER BLACK MATT

Battery operated wall switch

Art.no 4512694

GTIN 7071236015741

The Heatit Z-Push Wall Controller is a wireless wall-mounted Z-Wave Controller. It has mounting options for 1, 2 or 3 rockers, allowing for easy and practical management of your Z-Wave products. The switch can be set up to control scenarios or work in association with other Z-Wave products. Each rocker switch has a dual-color LED to indicate button actions.

The Wall Controller is coin cell battery powered. The product is intended primarily for residential applications.

Supplied in glossy white and black matt finish.

PRODUCT FEATURES

- Z-Wave
- Fits System 55 frames
- SmartStart
- Wireless battery-operated wall switch
- Designed for controlling lights, blinds, relays, dimmers etc.
- Controls up to 3 separate groups and 5 devices per group
- Easy to install with screws or double-sided adhesive tape
- Supports encryption modes S0, S2 Authenticated Class, S2 Unauthenticated Class
- 10 scene triggers per rocker
- Firmware update (OTA)

PRODUCT DATA

Colour	Black
Min. and max ambient humidity (RH%)	10 to 85%
Ambient temperature range in use	5 to 40°C
Ambient temperature range in storage	0 to 40°C

STANDARDS

Certification	RoHS, Reach
IP Code	IP20

WARRANTY

Warranty international	2 years
------------------------	---------

IOT / SMART HOME SPECIFIC DATA

Z-Wave Frequency	Z-Wave - 868.4 MHz (EU)
Z-Wave Chip	Z-Wave 700 chip
Min radio frequency range	40m
Over The Air update (OTA)	Yes
Push buttons	1, 2 or 3
Z-Wave encryption mode	S2 Unauthenticated Class S2 Authenticated Class S0

ELECTRO TECHNICAL DATA

Voltage	Battery
Battery type	CR2450 3V
Number of batteries required	1
Battery current	3V



PRODUCT DIMENSIONS

Product height/diameter	50mm	Product Width	100mm
Product length	110mm	Product net weight	140g

MAINTENANCE

The device is maintenance-free. Indoor use only.

ADDITIONAL INFORMATION

The product must be used with a security-enabled Z-Wave Controller in order to fully utilize security/encryption.

Supplied with 1, 2 or 3 rockers.

PRODUCT INFO RETURN AND RECYCLING

The product must be recycled as electronic waste.

DISCLAIMER

Warranty does not apply to batteries.

We develop and design our products according in accordance with our strict quality requirements (ISO 9001) and environmental requirements (ISO 14001).

All electrical installations must be carried out by an authorized electrical installer. The product must be installed in accordance with our installers manual and national building codes. Any wrongful installation, misuse, damage of the product, is not covered under warranty.

Updated documentation is available at www.heatit.com and/or documents.heatit.com

Heatit Controls AB can not be held liable for any type of errors or omissions in our product information.

Product specifications may change without further notice.



Heatit Z-Push Wall Controller Black Matt can be ordered from www.heatit.com/4512694

All additional documentation are available on the above adress and on documents.heatit.com/4512694

